



## Datasheet sonnenBatterie protect 1300

With sonnenBatterie protect you are safe even if the power fails. This accessory makes sure that the sonnenBatterie can continue to provide an integrated plug with power and the connected electrical consumer can proceed as usual.\*

	protect 1300 eco 8.2	protect 1300 eco 9.2
Inverter maximum power in VA (max. 2 sec)	2,500	2,500
Inverter power rating/continuous output in VA	1,300	
Output voltage	230 VAC / +/-10% / 50 Hz	
Operating form	1 phase on L1 / automatic switchover to emergency power	
Switchover (approx.)	3 seconds	
Weight in kg	0,8	
Ambient temperatures	5° – 30° C	
Dust and water protection	IP 21	
Dimensions (width x height x depth) in cm	15/19/12	
Protection functions	Overload, overcurrent, overtemperature	
GFCI	internal	
N-PE-connection	internal	
Phases	1	

We reserve the right to update or modify any information. All values, information, images and illustrations in this data sheet, brochures and all other publications are exemplary and are subject to on-going changes and updates. Unless expressly designated as binding all this information is provided with no assurances. Only the specifications in the binding order acceptance or the purchase contract are valid.

\* If the device is turned off, there is no tension on the protect 1300. The possession of a sonnenBatterie eco 8.2 / eco 9.2 is precondition to install the sonnenBatterie protect 1300. Item number on request.